



בקר כניסה קורא כרטיסי קרבה RFID מתקדמת מבית ביוקום ישראל עם בקר מוכלל.

בקר הכניסה כולל בקר מוכלל להחקנה קלה, אפשרות הורדת נתונים ישירות מהמכשיר באמצעות דיסק און קי, חיוי קולי ייחודי בעברית ועוד.

המערכת בעלת יכולת עבודה עצמאית ללא מחשב באמצעות שליטה מלאה וידידותית למשתמש על גבי המערכת, עם חיבור למנעול החשמלי באופן ישיר בלבד.

יחידת ה-S30 עובדת בסביבות מגוונות כגון רשת האינטראנט והאינטרנט באמצעות תוכנת בקר כניסה מקצועית (אופציונאלית בחשולם נפרד) אשר פותחה ע"י מהנדסי ביוקום, ומוחקנת כיום בארגונים הגדולים והחשובים בישראל.

### specifications:

User capacity	10,000 RFID users
Transaction capacity	30,000
Access mode	Card Only, PIN Only, Card+PIN
Access Control	50 Time Zone, 5 Grouping, 10 Combination, support stand alone
Electric lock control	Directness relay output 3A/12VDC
Communication	TCP/IP
Keyboard	4*4 metal keypad with 4 function keys
Power	12V DC,400MA
Read Range	10-15cm
USB	Mini USB 2.0
LCD Panel	4 line, 16 character
Measurement & Weight	194(L)*98(W)*50(D)mm
Temperature operating	0° - 45°
Humidity operating	20%-80%

[www.biocom.co.il](http://www.biocom.co.il)